

allegro²

connector protector



installation instructions

The Allegro connector protector kit provides extra protection for the ports in the I/O module at the bottom of the handheld. It works with the Allegro² and the Allegro³, hereafter referred to as the Allegro.

Copyright April 2019, Juniper Systems, Inc. Information is subject to change without notice. Juniper Systems, Allegro², and Allegro³ Rugged Handhelds are trademarks of Juniper Systems, Inc.

Kit: 25425



Contents of the Allegro²/Allegro³ Connector Protector Kit

The connector protector kit includes:

- Connector protector
- Instruction sheet

Installation Instructions

The large end of the connector protector is inserted into the connector module. The smaller end is the retention end, which is installed inside the battery compartment.

1. Power off the handheld.
2. Loosen the four captive screws holding the battery compartment door in place using a #1 Phillips screwdriver. Remove the door.



CAUTION: The Allegro is not sealed against water and dust when the battery door is not installed.

3. If you are replacing an existing connector protector, pull it off of the connector module and peel the retention end free.



4. To install the new connector protector, insert the retention end into the area below the connector module. Press it under the battery door screw holes as shown.

When the retention end is installed correctly, it will look like the following photo.



5. Place the Li-Ion battery pack in the compartment. Make sure the symbols on the battery pack label align with the symbols inside the compartment.
6. Re-install the battery door and tighten the screws. The door holds the connector protector in place.
7. Place the connector protector onto the connectors as shown.

